

Dämpfungswerte der Antennensteckdose Art.-Nr. 0232

| | | | Dämpfung in dB | | |
|--------------------|-----------------|-----------|----------------|--------|-----|
| | | | 0232 | | |
| | Frequenzbereich | | FM | TV | SAT |
| | MHz | | dB | dB | dB |
| Durchgangsdämpfung | 4-40 | Rückkanal | - | - | - |
| | 47-68 | VHF I | - | - | - |
| | 87,5-108 | FM | - | - | - |
| | 111-139 | Digiton | - | - | - |
| | 125-470 | VHF | - | - | - |
| | 470-862 | UHF | - | - | - |
| | 950-2050 | SAT | - | - | - |
| | 2050-2400 | SAT | - | - | - |
| Anschlußdämpfung | 4-40 | Rückkanal | - | - | - |
| | 47-68 | VHF1 | - | 1,5 | - |
| | 87,5-108 | FM | 1,5 | - | - |
| | 111-139 | Digiton | - | - | - |
| | 125-470 | VHF | - | 1.5* | - |
| | 470-862 | UHF | - | 1.5 | - |
| | 950-2050 | SAT | - | - | 2,0 |
| | 2050-2400 | SAT | - | - | - |
| Fernspeisbar | | mA | | 500 mA | |

* ab 175 MHz